

**SITA 200 PLUS
REPEATER PANEL**

The Sita Repeater panel provides additional indication and control for your system

The Sita repeater panel utilises a 2 core screened fire cable for data transmission, and will operate up to 4 repeater panels.

The panel gives full text and led indication of events taking place, and provides system controls for 'Alarms On/Off' and 'Reset System'.

The repeater panel housing is similar to the main control panel, allowing flush or surface mounting, complete with integral PSU and battery compartment.



Technical specifications

Compatibility:	Sita 200 plus	
Construction:	Front:	V2 rated ABS
	Back box:	Mild Steel
Operating Temperature:	5°C to 33°C	
Mains voltage:	230v AC +10% -15%	
Panel Inputs/Outputs:	1 x common fire relay	
	1 x common fault relay	
	1 x R-bus (Repeater and PC link)	
Battery Requirements:	2 x 3.3Ah 12v	
Part Code:	503 0002	

